

Disposal

The applicable environmental protection regulations must be observed. Do not dispose of batteries and electrical devices in household waste. Used batteries must be removed from the device without being destroyed and disposed of separately.

Packing material

Packaging materials must be recycled. You can also give packaging material to the distributor or trade professional for disposal free of charge at the place of handover.

Batteries



Battery contains lithium

The product contains batteries. Batteries must be removed from the product (instructions) and disposed of separately. Used batteries and accumulators should not go in household waste and can be returned to any local collection point free of charge. You are legally obliged to recycle used batteries.

Product

WEEE-Reg.-Nr. DE 69404980

The product must be properly disposed of as electronic scrap after use and to be dropped off at a local collection point, free of charge, for recycling of the materials, without obligation to make a new purchase.

For further details, see ElektroG3 §17(1)(2).



The **EU declaration of conformity** is available in the download area of www.assaabloy.com/de.

IKON
ASSA ABLOY

eCLIQ

User instructions

N109

Please check the functionality of the battery regularly!

Experience a safer
and more open world

Dear User, Thank you for choosing eCLIQ!



Note:

1. Your key is a high quality electronic product.
Protect the key from dirt and moisture.
2. In the event of malfunction due to moisture,
wipe the key dry only.
3. When the cylinder is actuated, there is a release delay of
approx. 0.1 seconds due to energy and data transmission.
This time can be 0.3 seconds if the battery is low.

4. Replace the battery within 30 seconds:

The time stored in the key is retained for 30 seconds (only V=E2 and V=E3). We recommend updating the key on the programming device after replacing the battery.

5. Battery life:

User key 100,000 locking operations
over approximately 10 years.

Beluga key 20,000 locking operations,
B1=7 years, B2/B3=5 years.

The standard eCLIQ battery VB04 is not approved for ATEX.
Use only special battery NV20.

The battery must not be replaced in the BELUGA version.

6. Ambient temperature key:
-30 °C to +50 °C
7. Key with feature "ATEX=II 2G Ex ib IIB T4 Gb".
For use in explosive areas of zone 1

Ex II 2G Ex ib IIB T4 Gb
IBExU14ATEX1125X

The key sends signals as soon as it is inserted in the cylinder.

Comment	Acoustic signal	Visual signal
Normal mode	–	–
Battery low, replace	3 x long	3 x long green
Locking authorisation OK	1 x short	1 x short green
No locking authorisation	3 x short	3 x short red
No locking authorisation because the key is currently outside of the time zone	3 x short	3 x short red-green-red
Update of authorisation (only relevant for eCLIQ GO systems)	1 x short, 1 x long	1 x short green, 1 x long green