# **ENVIRONMENTAL PRODUCT DECLARATION**

as per ISO 14025 and EN 15804

Owner of the Declaration ASSA ABLOY AB

Programme holder Institut Bauen und Umwelt e.V. (IBU

Publisher Institut Bauen und Umwelt e.V. (IBU)

Declaration number EPD-ASA-20150156-IBA1-EN

Issue date 10.06.2015

Access Control Systems – Aperio AH40 Hub
ASSA ABLOY AB







## **General Information**

## **ASSA ABLOY AB**

## Programme holder

IBU - Institut Bauen und Umwelt e.V. Panoramastr. 1 10178 Rerlin Germany

#### **Declaration number**

EPD-ASA-20150156-IBA1-EN

## This Declaration is based on the Product **Category Rules:**

IBU: PCR Electronic Access Control Systems, 11-2013 (PCR tested and approved by the independent expert committee (SVA))

#### Issue date

10.06.2015

#### Valid to

09.06.2020

Menmanes Prof. Dr.-Ing. Horst J. Bossenmayer

(President of Institut Bauen und Umwelt e.V.)

Dr.-Ing. Burkhart Lehmann (Managing Director IBU)

## Aperio AH40 Hub

#### Owner of the Declaration

ASSA ABLOY AB Förmansvägen 11 SE-117 43 Stockholm Sweden

#### Declared product / Declared unit

This Declaration represents the Aperio AH40 hub including all market configurations and shipping

#### Scope:

The Life Cycle Assessment is based on data collected from the Escatec facility in Penang, Malaysia.

The owner of the declaration shall be liable for the underlying information and evidence; the IBU shall not be liable with respect to manufacturer information, life cycle assessment data and evidences.

#### Verification

The CEN Standard EN 15804 serves as the core PCR Independent verification of the declaration and data according to ISO 14025

externally



## **Product**

#### **Product description** 2.1

The Aperio AH40 hub, produced by ASSA ABLOY AB, is an accessory to the Aperio Wireless lock product range. The Aperio hub acts as a gateway between the Aperio Wireless lock and the OEM electronic access control system passing credential data in one direction and access decision in the other.

The Aperio hub communicates wirelessly via a IEEE 802.15.4 based radio interface towards the Aperio wireless reader and through a wired interface towards the OEM electronic access control system. The Aperio AH40 hub uses a wired RJ45 Ethernet interface towards the OEM electronic access control system.

## Wireless interface

- IEEE 802.15.4 based interface running on the 2.4 GHz band
- ASSA ABLOY proprietary protocol on top of /IEEE 802.15.4/ for the Aperio application

### Wired interface

• RJ45 10 BASE-T/100 BASE-TX Ethernet interface supporting PoE according to IEEE 802.3af

## Other functions

- · Jumper block for configuration of internal/external antenna.
- · LED for operational state indication

#### **Application** 2.2

Dr. Wolfram Trinius

The Aperio hubs are suitable for indoor use. Common applications include: Commercial buildings, Industrial buildings, Government buildings, Education establishments, Healthcare buildings.

#### **Technical Data** 2.3

The table presents the technical properties of Aperio AH40 hub:

#### **Technical data**

Tooliilloai aata		
Name	Value	Unit
Power supply or		
PoE IEEE 802.3af	8-24	VDC
compliant class 1		
Power rating	3.5	W
Radio standard/ frequency	IEEE 802.15.4	MHz
range	(2400-2483,5)	IVITIZ
Receiver sensitivity	-100	dBm
Receiver sensitivity	-100	20%PER
Wireless transmitt power	10	dBm/ MHz
Wireless range	Up to 25	m
Operating Temperature	5-35	°C
Humidity	< 95 (non-condensing)	%



#### 2.4 Placing on the market / Application rules

#### **Compliance with US and Canadian Directives**

 UL294 ed 5 The Standard of Safety for Access Control System Units

## **Compliance with European Union Directives**

For the placing on the market of the products in the EU/EFTA (with the exception of Switzerland) the following harmonization legislation of the European Union applies:

 Directive 2014/53/EU of the European Parliament and of the Council of 16 April 2014 on the harmonisation of the laws of the Member States relating to the making available on the market of radio equipment and repealing Directive 1999/5/EC (R&TTE Directive).

The products are subject to CE marking according to this harmonization legislation. Affixing the CE marking to the products means the compliance of the products with the RoHS directive.

The following standards should be taken into account:

- EN 60950-1: 2006 Information technology equipment - Safety – Part 1: General requirements
- EN 301 489-1/ V1.9.2 Common Technical requirements
- EN 301 489-17/ V2.2.1 Electromagnetic compatibility and Radio spectrum Matters (ERM); ElectroMagnetic Compatibility (EMC) standard for radio equipment; Part 17: Specific conditions for Broadband Data Transmission Systems
- ETSI EN 300 328/ V1.8.1 Electromagnetic compatibility and Radio spectrum Matters (ERM); Wideband transmission systems; Data transmission equipment operating in the 2,4 GHz ISM band and using wide band modulation techniques; Harmonized EN covering the essential requirements of article 3.2 of the R&TTE Directive

## **FCC Certification:**

- 47 CFR §15.225 Sub part B & C Operation within the band 2400-2483 MHz
- RSS-210 Issue 8: 2010 License-exempt Radio Apparatus (All Frequency Bands): Category I Equipment - Spectrum Management and Telecommunications Radio Standards Specification

## **RoHS Conformity:**

 EN 50581:2012 Technical documentation for the assessment of electrical and electronic products with respect to the restriction of hazardous substances

## 2.5 Delivery status

The Aperio AH40 hub is shipped in a single package box which includes the Aperio hub, mounting plate, screes and installation manual. The dimension of the Aperio hub is (82mm x 82mm x 37 mm), the dimension of the single package box is (125mm x 125mm x 64mm). The shipment is done to ASSA ABLOY factories where the Aperio hubs are further co-shipped with Aperio wireless readers and accessories.

## 2.6 Base materials / Ancillary materials

The average composition of the Aperio AH40 hub is as following:

Component	Percentage in mass (%)
Plastics	50.71
Steel	1.49
Electronic	44.06
Electro-mechanic	2.99
Other	0.75
Total	100.0

#### 2.7 Manufacture

The Aperio AH40 hub is assembled at the production facility at Escatec Penang in Malaysia. The electronic components, including PCB, are purchased externally and assembled at Escatec. The plastic housing is supplied by another Escatec entity in Penang. The assembled PCBs are supplied by Eline PCB Sdn Bhd which is located in Malaysia. During assembly the individual parts are assembled into the hub casing. The assembled Aperio hub is then packaged with the mounting plate, installation accessories, and installation manual for shipment.

# 2.8 Environment and health during manufacturing

The Management System of Escatec has assessed and certified as meeting the requirements of ISO 14001:2004.

#### 2.9 Product processing / Installation

Aperio hubs are together with Aperio wireless locks installed by trained product integrators or installers. They can technically be installed by end users as well but that is not the norm case.

## 2.10 Packaging

The reader is packed in plastic and is fixated in the single package box together with installation accessories and installation instructions. Packaging materials shall be collected separately for recycling.

Material	Value (%)
Cardboard/ Paper	96.1
Plastics	3.9
Total	100.0

Packaging components incurred during installation are directed to energy recovery circuits.

- EWC 15 01 01 Paper and cardboard packaging
- EWC 15 01 02 Plastic packaging.

#### 2.11 Condition of use

No auxiliary or consumable materials are incurred for maintenance and usage of the reader. Repairs or replacement are not usually necessary. No cleaning efforts need to be taken into consideration.

## 2.12 Environment and health during use

There are no interactions between products, the environment and health.

#### 2.13 Reference service life

The service life of the Aperio Hubs is estimated to be 7 years. The 7 years is based on the support & service life of the Aperio Hub and neither factual nor estimated life time..

#### 2.14 Extraordinary effects

#### Fire

The external housing of the Aperio AH40 hub consists of a cover and mounting plate, are constructed from ABS. The housing material has been classified as having a UL94 HB Flame Rating. A UL94 Flame Rating of HB indicates: slow burning on a horizontal specimen; burning rate < 76 mm/min for thickness < 3 mm and burning stops before 100 mm.

## Water



No substances are used which have a negative impact on ecological water quality on contact by the device with water

#### **Mechanical destruction**

No danger to the environment can be anticipated during mechanical destruction.

## 2.15 Re-use phase

The following possibilities arise with reference to the material composition of the reader.

#### Re-use

During the reference service life the reader can be disconnected and dismounted then remounted and attached elsewhere.

#### Material Recycling

The ASSA ABLOY factories provide arrangements for the collection, treatment, recycling and recovery of the Aperio Hubs sold.

Waste codes according to European Waste Catalogue and Hazardous Waste List - Valid from 1 January 2002.

 EWC 16 02 13\* discarded equipment containing hazardous components other than those mentioned in 16 02 09 to 16 02 12

- EWC 16 02 14 Discarded equipment other than those mentioned in 16 02 09 to 16 02 13
- EWC 16 02 16 Components removed from discarded equipment other than those mentioned in 16 02 15
- EWC 17 02 03 plastic
- EWC 17 04 05 iron and steel
- EWC 17 04 11 Cables with the exception of those outlined in 17 04 10

Disposal of the product is subject to the WEEE Directive within Europe, Directive 2012/19/EU.

#### 2.16 Disposal

No disposal is foreseen for the product nor for the corresponding packaging.

#### 2.17 Further information

More information on ASSA ABLOY and Aperio is available from:

ASSA ABLOY AB Förmansvägen 11 SE-117 43 Stockholm Sweden Tel: +46 8 775 1860

Internet: www.assaabloy.com/aperio

## 3. LCA: Calculation rules

#### 3.1 Declared Unit

The declaration refers to the functional unit of 1 piece of Aperio AH40 hub as specified in Part B requirements on the EPD for Electronic Access Control Systems IBU PCR Part B.

#### **Declared unit**

Name	Value	Unit
Declared unit	1	piece of Aperio AH40 hub
Mass (without packaging)	0.134	kg
Conversion factor to 1 kg	7.47	-

## 3.2 System boundary

Type of the EPD: cradle to gate - with options. The following life cycle phases were considered for Reader:

A1-A3 Production stage:

- A1 Raw material extraction and processing
- A2 Transport to the manufacturer and
- A3 Manufacturing.

## Construction stage:

- A4 Transport from the gate to the site
- A5 Packaging waste processing

Use stage related to the operation of the building includes:

B6 – Operational energy use (Energy consumption)

## End-of-life stage:

- C2 Transport to waste processing.
- C3 Waste processing for recycling and
- C4 Disposal (landfill).

These information modules include provision and transport of all materials, products, as well as energy and water provisions, waste processing up to the end-of-waste state or disposal of final residues.

#### Module D:

 Declaration of all benefits or recycling potential from EoL and A5.

## 3.3 Estimates and assumptions

#### Use phase:

For the use phase, it is assumed that the lock is used in European Union, thus an EU electricity grid mix is considered within this stage.

#### EoL:

In the End-of-Life phase, for all the materials, which can be recycled, a recycling scenario with 100% collection rate was assumed.

## 3.4 Cut-off criteria

In the assessment, all available data from the production process are considered, i.e. all raw materials used, auxiliary materials (e.g. lubricants), thermal energy consumption and electric power consumption - including material and energy flows contributing less than 1% of mass or energy (if available). In case a specific flow contributing less than 1% in mass or energy is not available, worst case assumption proxies are selected to represent the respective environmental impacts.

Impacts relating to the production of machines and facilities required during production are out of the scope of this assessment.



#### 3.5 Background data

For life cycle modeling of the considered products, the GaBi 6 Software System for Life Cycle Engineering, developed by PE INTERNATIONAL AG, is used GaBi 6 2013. The GaBi-database contains consistent and documented datasets which are documented in the online

GaBi-documentation GaBi 6 2013D.

To ensure comparability of results in the LCA, the basic data of GaBi database were used for energy, transportation and auxiliary materials.

#### 3.6 Data quality

The requirements for data quality and background data correspond to the specifications of the IBU PCR PART A.

PE INTERNATIONAL performed a variety of tests and checks during the entire project to ensure high quality of the completed project. This obviously includes an extensive review of project-specific LCA models as well as the background data used.

The technological background of the collected data reflects the physical reality of the declared products. The datasets are complete and conform to the system boundaries and the criteria for the exclusion of inputs and outputs.

All relevant background datasets are taken from the GaBi 6 software database. The last revision of the used background data has taken place not longer than 10 years ago.

#### 3.7 Period under review

The period under review is 2013/14 (12 month average).

#### 3.8 Allocation

Regarding incineration, the software model for the waste incineration plant (WIP) is adapted according to the material composition and heating value of the combusted material. Following specific life cycle inventories for the WIP are considered:

- Waste incineration of plastic
- Waste incineration of paper
- Waste incineration of electronic scraps (PWB)

Regarding the recycling material of metals, the metal parts in the EoL are declared as end-of-waste status. Thus, these materials are considered in module D. Specific information on allocation within the background data is given in the GaBi dataset documentation.

## 3.9 Comparability

Basically, a comparison or an evaluation of EPD data is only possible if all the data sets to be compared were created according to EN 15804 and the building context, respectively the product-specific characteristics of performance, are taken into account.

## 4. LCA: Scenarios and additional technical information

The following technical information is a basis for the declared modules or can be used for developing specific scenarios in the context of a building assessment if modules are not declared (MND).

Transport to the building site (A4)

Name Value Unit											
		Unit									
Truck transport											
Litres of fuel diesel with maximum load (27 t payload)	39.4	l/100 km									
Transport distance truck	839	km									
Capacity utilization (incl. empty runs) of truck	85	%									
Ship transpo	ort										
Volume of heavy fuel oil with maximum load (27500 DWT)	5.3	m³/100 km									
Transport distance ship	5500	km									
Plane transp	ort										
Volume of kerosene with maximum load (113 t payload)	5.8	m³/100 km									
Transport distance plane	4500	km									
Gross density of products transported	-										
Capacity utilisation volume factor	-										

Installation into the building (A5)

mistanduon into the banding (Ab)		
Name	Value	Unit
Output substances following waste treatment on site Packaging (paper and plastic)	0.09	kg
Reference service life		
Nama	Value	Hnit

Name	Value	Unit
Electricity consumption	215	kWh
Days per year in use	365	d
Hours per day in on mode	24	h
Power consumtion per mode in W	3.5	W

## End of life (C1-C4)

Name	Value	Unit
Collected separately Steel, electronic, electro mechanics, plastic parts	0.134	kg
Collected as mixed construction waste construction waste for landfilling	0	kg
Reuse plastic	0.07	kg
Recycling Steel, Electronics, Electro mechanics	0.064	kg
Landfilling construction waste for landfill	0	kg

# Reuse, recovery and/or recycling potentials (D), relevant scenario information

relevant Scenario information		
Name	Value	Unit
Collected separately waste type (including packaging)	0.223	kg
Recycling Steel	0.90	%
Recycling/Reuse Electronic	26.41	%
Reuse Plastic parts	30.39	%
Recycling others	0.45	%
Reuse packaging (plastic + paper) (from Module A5)	40.06	%

## Operational energy use (B6)

Reference service life



# 5. LCA: Results

Results shown below were calculated using CML 2000 – Apr. 2013 Methodology.

DESC	RIPT	ION O	F THE	SYS	TEM	BOU	ND	ARY	(X = I)	NCL	UDE	ED IN I	_CA; I	MND	) = N	IOD	ULE N	OT	DEC	LA	RED)	
			CONOT	FDLIOTI																FITS AND		
PROD	OUCT S	STAGE	CONST ON PR					ι	JSE ST	AGE				END OF LIFE STAGE						LOADS BEYOND THE		
			STA	AGE																SY	'STEM	
																					NDARYS	
_		Iransport  Manufacturing  Transport from the gate to the site  Assembly				4.		1	F	١.,	rg)	ter	n			ing						
Raw material supply	Ĕ	iri	m sit	<u>&gt;</u>			2		Replacement <sup>1)</sup>		ien	ene	Operational water use	De-construction	ج۱	Ĕ	Waste processing		_	. :	- 6 <del>-</del>	
w mate supply	Transport	ctu	t fro	gu	) e		<u>a</u>	Repair	l ŭ		hr	onal e	ional	stru	demolition	Transport	900		Disposal	Reuse-	Recovery- Recycling- potential	
u dh	aus	Manufacturing ansport from th gate to the site Assembly Use		all	3ek	ace	:	DIS	ioi	ig si	suc	Ĕ۱	aus	br.		ds	ge ç	ote				
ay (	F	lan	nsp ate	Ϋ́		5	<u>                                      </u>	_	ер	Replacement ' Refurbishment 1) Operational energy		Frat	era	о-е -е	8	Ė	ıste	(	٦ ,	_ 2	x x a	
_		2	Tra						œ	(	ř	odc	o	Δ			Wa					
A1	A2	A3	A4	A5	B1	В	2	В3	B4	. E	35	В6	B7	C1		C2	C3	(	C4		D	
Х	Χ	Х	Х	Х	MN	D MI	ND	MND	MNI	D M	ND	Х	MND	MN	D	Χ	Х		Х		Χ	
RESU	LTS	OF TH	IE LCA	4 - EN	IVIRO	ONME	ENT	AL IN	/РАС	T: O	ne	piece (	of Ape	rio	AH4	-0 Ηι	ıb					
Parame	tor	Par	ameter			Jnit		<b>41-3</b>	A	4		A5	В6			22	СЗ		C4		D	
								-														
GWP		lobal war			[kg C	O <sub>2</sub> -Eq.]	1.4	6E+01	2.66	E-03	1.3	2E-01	1.02E	+02	7.38	E-03	6.44E-0	03	1.84E-	01	-1.60E+00	
ODP	stı	epletion pratosphe	ric ozone	layer		C11-Eq	.] 2.9	91E-09	1.39	E-12	5.8	7E-13	6.98E	-08	1.41	E-12	4.41E-1	12	5.50E-	13	-8.79E-11	
AP			d water		[kg S	O <sub>2</sub> -Eq.]	7.6	64E-02	1.24	E-05	3.0	3E-05	4.81E	-01	3.44	E-05	3.04E-0	05	5.03E-	05	-1.72E-02	
EP	E	Eutrophica	ation potentia		[kg (PC	O₄) <sup>3-</sup> - Eq	.] 5.9	9E-03	1.01	E-06	5.0	4E-06	2.71E	-02	6.16	E-06	1.71E-0	06	5.03E-	06	-1.01E-03	
POCE			heric ozor	ne	[kg Et	hen Eq.	5.0	8E-03	7.45	E-07	2.0	9E-06	2.86E	-02	-7.20	DE-06	1.81E-0	06	2.65E-	06	-9.03E-04	
ADPE			il resour	ces	įkg s	Sb Eq.]	9.3	80E-04	3.20	E-10	2.8	6E-09	1.41E	-05	5.01	E-10	8.92E-1	10	1.60E-	08	-1.17E-03	
ADPF	Abio	otic deple fossil ı			[]	MJ]	1.7	7E+02	3.87	3.83E-02		1.16E	1.16E+03 1.04E-01			7.32E-02 8.36E			02	-1.70E+01		
DECL	fossil resources					OURCE USE: One piece of Aperio AH40 H							b									
RESU	LTS	OF TH	IE LC/	4 - RE	SOU	RCE	US	E: Or	ne pie	ece c	of A	oerio <i>A</i>	\H40	Hub								
Parame			IE LCA Paramete		SOU	Unit		E: Or A1-3		A4	of Ap	oerio <i>A</i> A5	H40 I		C	2	СЗ		C4		D	
	ter Re	P enewable en	aramete primary ergy car	<b>er</b> / energy rier	y as				3		of Ap				C:	2	C3 -		C4 -		D -	
Parame	ter Re	Penewable	Paramete e primary ergy car ole prima	er / energy rier iry ener	y as	Unit		A1-3	<b>3</b> ⊦01		of Ap				C:	2	C3 -		C4 -		D -	
Parame PERE	Re Re	enewable en Renewab ources a tal use o	Paramete e primary ergy car ble prima as materi	er y energy rier rry energy al utiliza	y as gy ation	Unit		<b>A1-3</b> 1.51E+	<b>3</b> +01 +00				B6		-		<b>C3</b> 2.10E-0	2	-	03	D	
Parame PERE PERM	Re Re Tol	enewable enewable ources a tal use o ener on renewa	e primary ergy car ole prima as materi f renewa gy resou able primanergy ca	y energy rier lary energy able prinurces nary energy	y as gy ation mary ergy	Unit [MJ]		<b>A1-3</b> 1.51E+ 0.00E+	3 +01 +00 +01 6.	<b>A4</b> -		A5 -	B6		-		-	2	-	03	-	
Parame PERE PERM PERT	Res Total	enewable energenewable ources a tal use o energenewas e an renewa	e primary ergy car ole prima as materi f renewa gy resou able primanergy ca	y energy rier Iry energal utilization able prirurces nary energarrier	y as gy ation mary ergy	Unit [MJ] [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+	3 -01 -00 -01 6. -02	<b>A4</b> -		A5 -	B6		- 9.76E		-	2	- - 6.89E-0	)33	-	
Parame PERE PERM PERT	Ref. Ref. Ref. Res. Tool Ref. No.	enewable energenewable ources a tal use o energenewas e an renewa	Paramete e primary ergy car ole prima ss materi f renewa gy resou able prin energy ca able prin terial util of non r	y energy rier Iry energy al utilizable prinurces nary enarrier nary enaization ization	y as  gy ation mary ergy ergy ble	Unit [MJ] [MJ] [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+ 2.07E+	3 -01 -00 -01 6. -02 -00	<b>A4</b> -	3 3	A5 -	3.31E-	+02	- 9.76E	E-03	-		- - 6.89E-0 - -		-	
Parame PERE PERM PERT PENRI	E No	enewable en Renewab ources a tal use o ener in renew as e en renew as ma	Paramete e primary ergy car ble prima ss materi f renewa gy resou able prin nergy ca able prin terial util of non r energy re	y energy rier ury energy al utiliza able prin urces nary en- arrier nary en- lization renewak-	y as  gy ation mary ergy ergy ble es	Unit  [MJ]  [MJ]  [MJ]  [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+ 2.07E+ 0.00E+	3 -01 -00 -01 6. -02 -00 -02 5.	- - 91E-0	3 3		3.31E-	+02	- 9.76E -	E-03	- 2.10E-0: -	1	- - 6.89E-0 - -	)2 -	- -7.47E-01 -	
Parame PERM PERM PENRI PENRI PENRI	E No	enewable en	e primary ergy car ole prima sis materi f renewar gy resou able prin nergy ca able prin terial util of non renergy recondary	y energy rier ury energy al utilizable prin urces nary energy nary energy ization enewak esource y materi	y as  gy ation mary ergy ergy ble ess ial	Unit  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+ 2.07E+ 0.00E+ 2.07E+	3	91E-0 - - 18E-0	3 3 3 2 4 00 0.	.49E-03 - - .47E-02	3.31E- - - 1.81E-	+02 +03 +00 (	9.76E - - - 1.17E	E-03	- 2.10E-0; - - 1.15E-0	1	- 6.89E-0 - - 9.40E-0	02 -	- -7.47E-01 - - - -1.79E+01	
Parame PERM PERM PENRM PENRM PENRM PENRM SM	Fres No	enewable en Renewable ources a tal use o ener on renewa as ma Total use primary o Use of se se of rer	e primary ergy car ole prima sis materi f renewar gy resou able prin nergy ca able prin terial util of non renergy re econdary	y energy rier lay energy able prin larces nary en- energy en- en-energy en- en- en-energy en- en-energy en-en- en-en-en- en-en-en-en-en-en-en-en-en-en-en-en-en-e	y as gy ation mary ergy ergy else ial ary	Unit [MJ] [MJ] [MJ] [MJ] [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+ 2.07E+ 0.00E+ 2.07E+ 2.07E+ 0.00E+	3	91E-0 - - - - - - - 00E+0	22 4 400 0.00	A5	3.31E- - - 1.81E- 0.00E-	+02 +03 +00 (	9.76E - - 1.17E 0.00E	E-03 E-01 E+00 E+00	2.10E-0; - - 1.15E-0; 0.00E+0	1 0 0	- 6.89E-0 - - 9.40E-0	02 -	- -7.47E-01 - - - -1.79E+01 0.00E+00	
Parame PERE PERM PENRI PENRI PENRI PENRI SM RSF	Fres No	enewable en Renewab ources a tal use o ener on renew as e or renew as ma fotal use primary ouse of se of rer	e primary ergy car ole primas s materi f renewa gy resoo able prin nergy ca able prin terial util of non r energy r econdary newable fuels non ren	y energy rier Iry energal utilization to the able pringurces nary energarrier nary energization renewable esource y materi second	y as  gy ation mary ergy ergy ble es ial ary	Unit [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ]		A1-3 1.51E+ 0.00E+ 1.51E+ 2.07E+ 0.00E+ 2.07E+ 2.07E+ 0.00E+	3 -01 -00 -01 602 -02 502 000 000 0.	91E-0 - - - - - - - 00E+0	3 3 3 3 4 5 5 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	A5	3.31E- - - 1.81E- 0.00E-	+02 +03 +00 ( +00	9.76E - - 1.17E 0.00E	E-03 E-01 E+00 E+00	2.10E-0; - - 1.15E-0; 0.00E+0	1 0 0	- 6.89E-0 - - 9.40E-0 0.00E+0	00 00 00 00 00 00 00 00 00 00 00 00 00	-7.47E-01 	
Parame PERM PERM PENRM PENRM PENRM RSM RSF NRSF	RE NO NO T T U	Renewable en Renewable ources a tal use o ener en renewa as en renewa as ma Fotal use of see of rer	e primary ergy car ole prima as materi f renewa gy resoo able prin nergy ca able prin terial util of non r energy r econdary newable fuels non ren ondary f net fresi	y energy rier rry energy sal utiliza able prin urces nary energy nary energy ization enewak esource y materi second ewable uels h water	gy as gy attion mary ergy ergy ergy oble as	Unit [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ]		A1-:51E+ 1.51E+ 1.51E+ 2.07E+ 2.07E+ 2.07E+ 2.93E- 2.93E- 0.00E+ 7.41E-	3	A4 91E-0 118E-0 00E+0 00E+0 00E+0 65E-0	22 4 00 0.00 00 0.05 5 3	A5	3.31E- - 1.81E- 0.00E- 0.00E- 0.00E- 8.18E	+03 +00 ( +00 ( -01 )	- - - - 11.17F 0.00E 0.00E	E-03 E-01 E+00 E+00	2.10E-0: 1.15E-0 0.00E+0 0.00E+0	1 0 0	- - 6.89E-0 - - 9.40E-0 0.00E+0	00 00 00 00 00 00 00 00 00 00 00 00 00	- -7.47E-01 - - -1.79E+01 0.00E+00 0.00E+00	
Parame PERM PERM PENRM PENRM PENRM RSF NRSF FW	E NO U	Renewable en Renewable ources a tal use o ener en renewa as en renewa as ma Fotal use of see of rer	e primary ergy car ole primary ergy car ole primary ergy resou able primanergy cable primanergy cable primanergy cable primanergy recondary freecondary freecondar	y energy rier ry energy	gy as gy ation mary ergy ergy ole essial ary	Unit [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ]		A1-:51E+ 1.51E+ 1.51E+ 2.07E+ 2.07E+ 2.07E+ 2.93E- 2.93E- 0.00E+ 7.41E-	3	A4 91E-0 118E-0 00E+0 00E+0 00E+0 65E-0	22 4 00 0.0 00 0.0 55 3	A5	3.31E- - 1.81E- 0.00E- 0.00E- 0.00E- 8.18E	+03 +00 ( +00 ( -01 )	- - - - 11.17F 0.00E 0.00E	E-03 E-01 E+00 E+00	2.10E-0: 1.15E-0 0.00E+0 0.00E+0	1 0 0	- - 6.89E-0 - - 9.40E-0 0.00E+0	00 00 00 00 00 00 00 00 00 00 00 00 00	- -7.47E-01 - - -1.79E+01 0.00E+00 0.00E+00	
Parame PERM PERM PENRM PENRM PENRM RSF NRSF FW	Reference No.	enewable en Renewable ources a tal use o ener on renewa as en rotal use primary o Use of se se of rer Use of	Paramete e primary ergy car ele primary ergy car ele prima ses materi f renewas gy resou able prin nergy ca able prin terial util of non renergy re econdary newable fuels non ren ondary f net fresi  IE LCA erio Al	y energy rier ry energy	gy as gy ation mary ergy ergy ergy sial ary	Unit [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ] [MJ]	OW	A1-:51E+ 1.51E+ 1.51E+ 0.00E+ 1.51E+ 0.00E+ 2.07E+ 2.93E- 2.93E- 7.41E- S AN	3	A4 91E-0 118E-0 00E+0 00E+0 00E+0 65E-0	2 4 400 0.00 00 0.00 5 3	A5	3.31E- - 1.81E- 0.00E- 0.00E- 0.00E- 8.18E	+03 +00 ( +00 ( -01 )		E-03 E-01 E+00 E+00	2.10E-0: 1.15E-0 0.00E+0 0.00E+0	1 0 0	- - 6.89E-0 - - 9.40E-0 0.00E+0	00 00 00 00 00 00 00 00 00 00 00 00 00	- -7.47E-01 - - -1.79E+01 0.00E+00 0.00E+00	
Parame PERE PERM PENRI PENRI SM RSF NRSF FW RESU One p	E NO U	Renewable en Renewable ources a tal use o ener on renewa as en rotal use primary o Use of se se of rer Use of OF TH	Paramete e primary ergy car ele primary ergy car ele prima ss materi f renewas gy resou able prin nergy ca able prin terial util of non renergy re econdary newable fuels non ren ondary f net fresi  IE LCA erio Al	y energy rier ry energy	gy as gy ation mary ergy ergy ole essial ary	Unit  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]	OW	A1-:51E+ 11.51E+ 11.51E+ 22.07E+ 22.07E+ 22.07E+ 22.07E+ 32.07E+ 33.00E+ 34.00E+ 35.00E+ 36.00E+ 36.00E+	3	A4 91E-0	33 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3	A5	3.31E- - 1.81E- 0.00E- 0.00E- 8.18E	+02 +03 +00 ( +00 ( +00 (	9.76E	==-03 ==-01 ==+00 ==+00 ==-05	2.10E-0; - 1.15E-0; 0.00E+0 0.00E+0 0.00E+0 5.17E-0;	1 0 0 0 0 0 0 0 5 5	- 6.89E-0 - - 9.40E-0 0.00E+0 0.00E+0 0.00E+0	000 000		
Parame PERM PERM PENRI PENRI PENRI SM RSF NRSF FW RESU One p	Reference to the control of the cont	enewable enemals as ear renewals as ear renewals as ear renewals as ear of the total use of second of Apo	e primary ergy car ole primary ergy car ole primary ergy car ole primary ergy resource of non renergy recondary free ondary free fuels on the free ondary free ondary free ondary free free ondary free ondary free free ondary free ondar	y energy rier ry energy escond ewable ewable uels h water energy	gy as gy ation mary ergy ergy ble es ial ary JTPU lub	Unit  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]  [MJ]	OW	A1-:51E+ 11.51E+ 2.07E+ 2.07E+ 2.07E+ 2.07E+ 2.09E+ 7.41E- S AN Mit	3	91E-0	3 3 3 3 2 4 4 EE-06	A5	3.31E- 1.81E- 0.00E- 0.00E- 0.00E- 8.18E  PRIES 6 2.51	+02 +03 +00 ( +00 ( -01	9.76E 1.17E 0.00E 0.00E 1.85E	E-03 E-01 E-01 E-00 E-00 E-00 E-00	2.10E-0; - 1.15E-0; 0.00E+0 0.00E+0 0.00E+0 5.17E-0;  C3 1.59E-0	1 1 00 00 00 00 00 00 00 00 00 00 00 00	- 6.89E-0 - - 9.40E-0 0.00E+0 0.00E+0 0.00E+0	000 000	-7.47E-01 -1.79E+01 0.00E+00 0.00E+00 -9.76E-03	
Parame PERE PERM PENRI PENRI PENRI RSF NRSF FW RESU One p Param	Red	enewable enemals and several s	e primary ergy car ole primary ergy car ole primary ergy car ole primary ergy resource of the primary car ole primary car ole primary car ole primary car ole primary recondary recondary from the primary from th	y energy rier ry energy all utilization ary energy energy energy energy energy energy energy energy enewable esource y materi second ewable uels h water A — OU H40 H rametel waste our waste our energy ener	gy gation mary ergy ergy oble essal ary utility r	Unit  [MJ]	OW	A1-:51E+ 11.51E+ 11.51E+ 22.07E+ 0.00E+ 0.00E+ 0.00E+ 7.41E- 7.41E- 7.41E- 7.41E- 8.60E+ 9.60E+ 9.60	3	A4	33 3 3 2 2 4 4 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		3.31E- 1.81E- 0.00E- 0.00E- 8.18E  PRIES  6 2.51 3 5.86	+02		E-03 E-01 E-01 E-00 E-00 E-00 E-00 E-00	2.10E-0: - 1.15E-0: 0.00E+0 0.00E+0 0.00E+0 5.17E-0:  C3 1.59E-0 3.70E-0	11 100 000 000 000 000 000 000 000 000	- - 6.89E-0 - 9.40E-0 0.00E+( 0.00E+( 4.92E-0 <b>C4</b> 8.13E-( 1.90E-(	000 000		
Parame PERE PERM PENRI PENRI PENRI SM RSF FW RESU One p	Reference Service Serv	enewable en. Renewable en. Renewable ources a tal use o ener en renew. as e en renew. as mar fotal use primary elluse of sec use of Apol	Paramete per primary ergy car ergy car ergy car elle primary ergy car elle primary ergy car elle primary ergy resou able prin ergy ca able prin ergy re econdary newable fuels non ren ondary f net fres erio Al  Par zardous hazardou	y energy rier ry energy all utilization arrier mary energy enewatesource y materi second ewable uels h water 4 - OU 140 H construction was the construction arrived by the construction of	gy as gy ation mary ergy ergy ergy less all ary lub r dispose e dispose dispose	Unit  [MJ]	OW U	A1-:51E+ 1.51E+ 0.00E+ 1.51E+ 0.00E+ 2.07E+ 2.07E+ 2.93E- 2.00E+ 7.41E- S AN 1.51E+ 1.	3		33 3 3 2 2 4 4 4 E-06 E-05 E-06	.49E-0347E-02 .00E+00 .00E+00 .79E-04 ATEGO .3.08E-0 3.99E-0	3.31E 1.81E- 0.00E- 0.00E- 8.18E  0.00E- 0.00E- 8.18E  0.00E- 8.18E	+02 +03 +00 ( +00 ( -01 ::		E-01 E+00 E+00 E-05 Z2 Z2 Z6-06 BE-05	2.10E-0; - 1.15E-0; 0.00E+0 0.00E+0 0.00E+0 5.17E-0;  C3 1.59E-0 1.65E-0	1 1 00 00 00 00 00 00 00 00 00 00 00 00	- - - - - 9.40E-0 0.00E+( 0.00E+( 4.92E-0 <b>C4</b> 8.13E-( 1.90E-( 4.13E-(	002 - 000 000 000 000 000 000 000 000 00		
Parame PERE PERM PENRI PENRI SM RSF FW RESU One p Param HWM RWM	E No U U U U U U U U U U U U U U U U U U U	enewable enewable enewable ources a tal use o ener enewas ma se en renewas ma fotal use primary of use of sec Use of OF TH of Apol	Paramete e primary ergy car ole primary ole primary ole primary ole primary ole primary ergy resolution on on renergy re econdary newable fuels non ren ondary f net fresi  Pal  Zardous hazardous hazardous dioactive	y energy rier layener	y as  gy ation nary ergy ergy ergy  JTPL tub  r  dispos e dispos re-use	Unit  [MJ]	OW U	A1-:51E+ 1.51E+ 0.00E+ 1.51E+ 0.00E+ 2.07E+ 2.07E+ 2.07E+ 2.00E+ 3.000E+ 5.AN  iii // gg 5.6 2.00 gg 1.1.00 gg 0.00	3	A4  91E-0  18E-0  00E+C  00E+C  65E-0  ASTI  1.271  5.200  0.00E	33 3 3 3 2 2 4 4 3 5 5 5 3 3 5 5 6 5 6 5 6 6 6 5 6 6 6 6		3.31E- 1.81E- 0.00E- 0.	+02	9.76E 	E-03 E-03 E-01 E+00 E+00 E-05 E-05 E-06 E-06 E-06 E-06	2.10E-0; - 1.15E-0; 0.00E+0 0.00E+0 0.00E+0 5.17E-0;  C3 1.59E-0 1.65E-0	1 1 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	- - - - - 9.40E-0 0.00E+( 0.00E+( 4.92E-0 <b>C4</b> 8.13E-( 4.13E-( 0.00E+(	000 000 000 000 000 000 000 000 000 00		
Parame PERM PERM PENRI PENRI PENRI PENRI SM RSF INRSF FW RESU One p Param HWI NHM RWI CRI	Reference Refere	enewable en renewal as marotal use of secondaria enewable en renewal en r	Paramete e primary ergy car ole primary ergy car ole primary ergy car ole primary ergy car ole primary f renewa rgy resou able prin nergy ca able prin terial util of non r energy r econdary r econdary f non ren ondary f net fresl  Pal  zardous hazardous compone	y energy rier ry energy	gy as gy ation mary ergy ergy ole essial ary JTPU lub r dispose e disposere-use cycling	Unit  [MJ]	OW IN	A1-:51E+ 1.51E+ 2.07E+ 2.07E+ 2.07E+ 2.07E+ 2.09E+ 3.000E+ 3.0	3	A4  91E-0	22 4 00 0.0 00 0.0 00 0.5 5 3 6 E-06 E-05 E-06 E-05 E-06 E-05	A5	3.31E- 1.81E- 0.00E- 0.	+02	9.76E	E-01 E+00 E+00 E+00 E+00 E+00 E+00 E+00	- 2.10E-0: - 1.15E-0: 0.00E+0 0.00E+0 0.00E+0 5.17E-0:  C3 1.59E-0 3.70E-0 0.00E+0	1 1 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		202 - 2000 000 000 000 000 000 000 000 000 00	- -7.47E-01 - -1.79E+01 0.00E+00 0.00E+00 -9.76E-03 <b>D</b> -2.37E-04 -2.56E-02 -3.79E-04	
Parame PERM PERM PENRI PENRI PENRI PENRI SM RSF FW RESU One p Param HWI NHM RWI CRI	Reference Refere	Renewable en Renewable ources a tal use o ener on renew as ean renewable ources as tal use of tal use primary of tal use of second or tal use of tal use o	e primary ergy car ole primary ergy car ole primary ergy car ole primary ergy resource of non renergy recondary from the fuels of non renergy recondary from the fuels of non renergy from the fuels of non-fuels of fuels of the fu	y energy rier ry energy all utilization ary energy exacts a waste of waste of the energy electrica	gy g	Unit  [MJ]  [MJ]	OW UK	A1-:51E+ 1.51E+ 2.07E+ 2.07E+ 2.07E+ 2.07E+ 2.09E+ 7.41E- 2.93E- 0.00E+ 7.41E- 3.00E+ 7.41E- 3.00E+ 7.41E- 3.00E+ 7.41E- 3.00E+ 7.41E- 3.00E+ 7.41E- 3.00E+ 7.41E- 9.00E+	3	A4  91E-0 18E-0 00E+0 00E+0 00E+0  - 5.011 1.271 5.200 0.000 0.000	2 4 20 00 0. 3 3 3 22 4 400 0. 5 3 3 6 5 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	A5	3.31E- 1.81E- 0.00E- 0.00E- 0.00E- 8.18E  06 2.51 03 5.86 06 2.61 00 0.00 00 0.00 00 0.00	+02	9.76E	E-01	2.10E-0; - 1.15E-0 0.00E+0 0.00E+0 0.00E+0 5.17E-0;  C3 1.59E-0 3.70E-0 1.65E-0 0.00E+1 3.00E-0	1 1 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	- 6.89E-0 - 9.40E-0 0.00E+0 0.00E+0 0.00E+0 4.92E-0 - 1.90E-0 4.13E-0 0.00E+0 0.00E+0	006 : 006 : 000 000 000 000 000 000 000	- -7.47E-01 - -1.79E+01 0.00E+00 0.00E+00 0.00E+00 -9.76E-03 <b>D</b> -2.37E-04 -2.56E-02 -3.79E-04	



## 6. LCA: Interpretation

This chapter contains an interpretation of the Life Cycle Impact Assessment categories. Stated percentages in the whole interpretation are related to the overall life cycle, excluding credits (module D).

The production phase (modules A1-A3) contributes between 4% and 18% to the overall results for all the environmental impact assessment categories hereby considered, except for the abiotic depletion potential (ADPE), for which the contribution from the production phase accounts for app. 99% - this impact category describes the reduction of the global amount of non-renewable raw materials, therefore, as expected, it is mainly related with the extraction of raw materials (A1). Within the production phase, the main contribution for all the impact categories is the production of plastics and steel, with app. 49%, mainly due to the energy consumption on this process. Plastics and electronics account with app. 95% to the overall mass of the

product, therefore, the impacts are in line with the mass composition of the product. The environmental impacts for the transport (A2) have a negligible impact within this stage.

To reflect the use phase (module B6), the energy consumption was included and it has a major contribution for all the impact assessment categories considered - between 82% and 96%, with the exception of ADPE (1%). This high value is due to the 24 hours per day in on mode as stated in Chapter 4.

In the end-of-life phase, there are loads and benefits (module D, negative values) considered. The benefits are considered beyond the system boundaries and are declared for the recycling potential of the metals and for the credits from the incineration process (energy substitution).

# 7. Requisite evidence

Not applicable in this EPD.

#### 8. References

#### **Institut Bauen und Umwelt**

Institut Bauen und Umwelt e.V., Berlin (pub.): Generation of Environmental Product Declarations (EPDs);

#### **General principles**

for the EPD range of Institut Bauen und Umwelt e.V. (IBU), 2013-04 www.bau-umwelt.de

#### PCR Part A

Institut Bauen und Umwelt e.V., Berlin (pub.): Product Category Rules for Construction Products from the range of Environmental Product Declarations of Institut Bauen und Umwelt (IBU), Part A: Calculation Rules for the Life Cycle Assessment and Requirements on the Background Report. April 2013

www.bau-umwelt.de

## **IBU PCR Part B**

IBU PCR Part B: PCR Guidance-Texts for Building-Related Products and Services. From the range of Environmental Product Declarations of Institute Construction and Environment e.V. (IBU). Part B: Requirements on the EPD for Electronic Access Control Systems. <a href="https://www.bau-umwelt.com">www.bau-umwelt.com</a>

## EN 15804

EN 15804:2012+A1:2014: Sustainability of construction works — Environmental Product Declarations — Core rules for the product category of construction products

#### GaBi 6 2013

GaBi 6 2013: Software-System and Database for Life Cycle Engineering. Copyright, TM. Stuttgart, PE INTERNATIONAL AG, Leinfelden-Echterdingen, 1992-2013.

#### GaBi 6 2013D

GaBi 6 2013D: Documentation of GaBi 6: Software-System and Database for Life Cycle Engineering. Copyright, TM. Stuttgart, PE INTERNATIONAL AG, Leinfelden-Echterdingen, 1992-2013. http://documentation.gabi-software.com/

## ISO 14025

DIN EN ISO 14025:2011-10: Environmental labels and declarations — Type III environmental declarations — Principles and procedures

#### EN 50581:2012

RoHS Conformity: EN 50581:2012 Technical documentation for the assessment of electrical and electronic products with respect to the restriction of hazardous substances

#### EN 60950-1

EN 60950-1: 2006/ All:2009 +A1:2010 +A12:2011 Information technology equipment - Safety - Part1: General requirements

#### EN 301 489-1

EN 301 489-1 V1.9.2 Common Technical requirements

#### EN 301 489-17

EN 301 489-17 V2.2.1 Electromagnetic compatibility and Radio spectrum Matters (ERM); ElectroMagnetic Compatibility (EMC) standard for radio equipment; Part 17: Specific conditions for Broadband Data Transmission Systems

#### EN 300 328

EN 300 328 V1.8.1 Electromagnetic compatibility and Radio spectrum Matters (ERM); Wideband transmission systems; Data transmission equipment operating in the 2,4 GHz ISM band and using wide band modulation techniques; Harmonized EN covering the essential requirements of article 3.2 of the R&TTE Directive



#### **EWC**

European Waste Catalog

## 47 CFR §15.225

47 CFR  $\S15.225$ : 2012 Sub part B & C Operation within the band 2400-2483 MHz

#### RSS-210 Issue 8: 2010

RSS-210 Issue 8: 2010 License-exempt Radio Apparatus (All Frequency Bands): Category I Equipment - Spectrum Management and Telecommunications Radio Standards Specification

#### IEE 802.15.4

IEEE Standard for Local and metropolitan area networks – Part 15.4: Low-Rate Wireless Personal Area Networks

#### IEEE 802.3af

Amendment to the IEEE 802.2 ethernet standard for Power via Media Dependent Interface (MDI), i.e. Power Over Ethernet

#### ISO 14001:2004

Environmental management systems - Requirements with guidance for use (ISO 14001:2004 + Cor. 1:2009)

#### **UI 94 HB**

UL94 HB: slow burning on a horizontal specimen; burning rate < 76 mm/min for thickness < 3 mm and burning stops before 100 mm

#### **UL294 ed 5**

The Standard of Safety for Access Control System Units

## **R&TTE Directive**

Radio and telecommunications terminal equipment (R&TTE); 2014/53/EU



## 9. Annex

Results shown below were calculated using TRACI Methodology.

DESC	RIP	ΓΙΟΝ Ο	F THE	SYST	ΈМ	BOUN	DAI	RY (X	( = II	NCLUE	ED IN	LC	CA: MN	D = 1	MOD	ULE NO	T DE	CL/	(RED)								
																	FITS AND										
DDOL	NICT	STAGE		RUCTI OCESS				1101	≣ STÆ	ACE.				ENIC	OF LI		OADS										
FROL	0001	STAGE		AGE				USL	_ 317	-GL				LINL	OI L	_		YSTEM									
																		JNDARYS									
		_	e a						_	5	g	٩	<u>,</u>			gu											
rial	<u>.</u>	Manufacturing	ansport from th gate to the site	>		S S			Replacement <sup>1)</sup>	Refurbishment <sup>1)</sup>	Je I	Į,	use Use De-construction	ے	<b>–</b>	SSil	_		√ ₩−								
ate oly	<u>o</u>	l ig	fro he	lqu	Œ	ر   عور		a.	a E	Ē	<u> </u>	$\frac{1}{\alpha}$		i <u>ii</u>	ōd	000	Sa	-se-	rer; ilin itia								
Raw materia supply	Transport	Ta(	ort to t	Assembly	ls e	Maintenance		Repair	эсе	lsiq	onal	. i	use	demolition	Transport	pro	Disposal	Reuse-	Recovery- Recycling- potential								
s	Ë	auı	ısp ite	As		lair l		14	plde	] j	rati	ro-		ge	Ë	ste	ቯ	2	Re Po								
<u>~</u>		Σ	Transport from the gate to the site			2			ď	Re	Operational energy	Onerational water	<u> </u>			Waste processing											
A1	A2	A3	A4	A5	B <sup>.</sup>	1 B2		B3	B4	B5	B6			:1	C2	C3	C4		D								
X	X	X	X	X	MN			-	MND		X			ND	X	X X	X		X								
																	^		^								
		OF IF			VIR	ONMEN								AH <sup>4</sup>													
Paran			Parame			Uni		A1		A4	A		В6		C2	C3		:4	D								
GW	/P		l warming			[kg CO <sub>2</sub>	-Eq.]	1.46E	E+01	2.66E-0	3 1.32	≣-01	1.02E+0	02 7.3	88E-03	6.44E-03	3 1.84	E-01	-1.60E+00								
OD	P	stratos	tion pote spheric o	zone laye	er	[kg CFC1	1-Eq	3.12	E-09	1.47E-1	2 6.25	≣-13	7.42E-0	8 1.5	0E-12	4.69E-12	5.84	E-13	-1.32E-10								
AF	>	Acidifica	ation pote and wa		and	[kg SO <sub>2</sub>	-Eq.]	7.59	E-02	1.23E-0	5 3.66	≣-05	4.55E-0	1 4.1	4E-05	2.88E-0	5.98	E-05	-1.65E-02								
EF	>		phication			[kg N-e	eq.]	5.16	E-03	5.86E-0	7 2.03	≣-06	1.94E-0	2.6	9E-06	1.22E-06	3 2.32	E-06	-4.31E-04								
Sm	og	Ground	level smo- potenti		ion	[kg O <sub>3</sub> -	eq.]	9.62	E-01	1.59E-0	4 8.09	≣-04	4.12E+0	7.4	I0E-04	2.60E-04	7.00	E-04	-1.86E-01								
Resou	ırces			[MJ]		1.31E	E+01	3.90E-0	3 4.44	≣-03	8.24E+0	1.3	3E-02	5.21E-03	8.52	E-03	-8.29E-01										
RESU	JLTS	OF TH	IE LC <i>I</i>	4 - RE	sol	JRCE U	ISE:	One	pie	ce of A	perio	AH	l40 Hul	)													
Parame	eter	Р	aramete	er		Unit		A1-3		A4	A5		В6	С	2	СЗ	С	4	D								
PERE	R	enewable	e primary ergy car		as	[MJ]	1.5	51E+01		-	-		-		-	-	-		-								
PERM		Renewab	le prima	ry energ		[MJ]	0.0	00E+00	)	-	-			=		_											
PERT	To	sources a stal use o	f renewa	ıble prim		[MJ]	+			91E-03	3.49E-0	03 3.31E+02		+02 9.76E-03		76E-03 2.10E-02		E-03	-7.47E-01								
PENR	N/	on renewa		nary ene	rgy	[MJ]	-	)7E+02		_	_	. 102 00 0.0121															
PENR	NI	as e on renewa	nergy ca able prin		rgy	[MJ]	+-	00E+00		_				-													
		as mat Total use	terial util of non r		e	[MJ]	-					0 4															
	primary ene		primary e		rimary energy resources		primary energy resource		nergy resources			)7E+02			4.47E-0		.81E+03	1.17		1.15E-01	9.40		-1.79E+01				
SM				se of renewable secondary		Use of secondary material				<u> </u>		<u> </u>		[kg]		93E-02	1		0.00E+0		0.00E+00	0.001		0.00E+00	0.00		0.00E+00
RSF			fuels		,	[MJ]	-	00E+00			0.00E+0	-	0.00E+00	0.001		0.00E+00			0.00E+00								
NRSF		sec	non ren	uels		[MJ]			_			_	0.00E+00	<u> </u>		0.00E+00			0.00E+00								
FW			net fresl			[m³]		41E-02	_		3.79E-0		3.18E-01	1.85	E-05	5.17E-05	4.92	E-04	-9.76E-03								
						JT FLO	WS	AND	WA	STE C	ATEC	OF	RIES:														
One p	piece	of Ape	erio Al	H40 H	ub		1		1								_										
Param	eter		Pai	rameter			Unit	A1-	-3	A4	A	5	В6		C2	C3	C	4	D								
HW	D		zardous		•		[kg]	5.65E	-03	5.01E-0	3.08	-06	2.51E-0	1 5.1	7E-06		_	E-06	-2.37E-04								
NHM	۷D		nazardou				[kg]	2.05E		1.27E-0					8E-05	1	_	E-02	-2.56E-02								
RW			dioactive				[kg]	-					2.61E-0			1.65E-0	_	E-06	-3.79E-04								
CR			Compone				[kg]				_			_		0.00E+0			-								
MFI	R		Materials				[kg]			0.00E+0						3.00E-03			-								
ME			erials for			-							0.00E+0	_		0.00E+0			-								
EEI	E		ported e				[MJ]	0.00E	+00	0.00E+0	0 1.73	-01	0.00E+0	0.0	0E+00	0.00E+0	3.22	E-01	-								
EET Exported thermal e				Exported thermal energ					+00	0.00E+0	0 4.87	-01	0.00E+0	0.0	0E+00	0.00E+0	0 8.83	E-01	-								



#### **Publisher**

Institut Bauen und Umwelt e.V. Panoramastr. 1 10178 Berlin

Germany

Tel +49 (0)30 3087748- 0 Fax +49 (0)30 3087748- 29 Mail

info@bau-umwelt.com Web www.bau-umwelt.com



#### Programme holder

Institut Bauen und Umwelt e.V. Panoramastr 1 10178 Berlin Germany

Tel Fax Mail

+49 (0)30 - 3087748- 0 +49 (0)30 – 3087748 - 29 info@bau-umwelt.com Web www.bau-umwelt.com



## **Author of the Life Cycle Assessment**

PE INTERNATIONAL AG Hauptstraße 111

70771 Leinfelden-Echterdingen Germany

Tel +49 711 34 18 17 22 Fax +49 711 34 18 17 25

consulting@pe-international.com www.pe-international.com Mail Web



#### Owner of the Declaration

ASSA ABLOY AB Förmansvägen 11 SE-117 43 Stockholm Sweden

Tel +46 8 775 1860

Web www.assaabloy.com/aperio